

Block diagram for universal backplane 8 modules - 8/16 x I/O

The wiring shown in the table on the following page is 1:1 wiring with no components mounted in the signal chain.

Supported I/O modules:

9106xxx, 9107xx, 9113xx, 9116xx, 9202xxx and 9203xxxx.

Please note:

Check the module manual for correct Input/Output signal wiring.

Universal card wiring, 16 x uni. I/O, 2 channel modules

9___xxxxx Field equipment terminals		Non I.S. I/O terminal	SUB-D37 adaptor CN1
Unit	Ch.		
#1	1	Pin 11	Pin 20
		Pin 12	Pin 1
	2	Pin 13	Pin 21
		Pin 14	Pin 2
#2	1	Pin 11	Pin 22
		Pin 12	Pin 3
	2	Pin 13	Pin 23
		Pin 14	Pin 4
#3	1	Pin 11	Pin 24
		Pin 12	Pin 5
	2	Pin 13	Pin 25
		Pin 14	Pin 6
#4	1	Pin 11	Pin 26
		Pin 12	Pin 7
	2	Pin 13	Pin 27
		Pin 14	Pin 8
#5	1	Pin 11	Pin 28
		Pin 12	Pin 9
	2	Pin 13	Pin 29
		Pin 14	Pin 10
#6	1	Pin 11	Pin 30
		Pin 12	Pin 11
	2	Pin 13	Pin 31
		Pin 14	Pin 12
#7	1	Pin 11	Pin 32
		Pin 12	Pin 13
	2	Pin 13	Pin 33
		Pin 14	Pin 14
#8	1	Pin 11	Pin 34
		Pin 12	Pin 15
	2	Pin 13	Pin 35
		Pin 14	Pin 16