

## TC temperature input to bipolar mA / V output - 5115 5115 with bipolar output, +/- 20 mA or +/- 10 V

Configuration:

**PRetrans 5115A\_**

**Analog Input 1:**

Input Type: TC-K  
Input Range: 0...1000 °C  
Cold Junc. Comp.: Int. CJC

**Analog Output 1:**

Output Type: Current  
Output Function: Output = I1  
Output Range: 20...0 mA  
Output Limits: 0...20 mA

**Analog Input 2:**

Input Type: Current  
Input Range: 4...20 mA

**Analog Output 2:**

Output Type: Current  
Output Function: Output = I1  
Output Range: 0...20 mA  
Output Limits: 0...20 mA

JP1, JP2 in pos 1

Current output DP2.2 = OFF

Voltage output DP2.2 = ON

Wiring diagram:

